


XBASE

Moderate, multi-use fume extraction unit

PUREX

CLEAN AIR FOR EVERYONE



Description & features

- VariColour filter blocked warning system
- Highest grade HEPA and carbon technology
- Automatic electronic flow control - maintains a constant extraction rate even as the filter blocks
- Quiet in operation
- Simple to install and easy to relocate

Filters



Main Filter Code

113585

Description

HEPA/Chemical Special



Pre-Filter Code

111108

Description

F8/F9 Labyrinth

Specification

Voltage	120v	230v
Part Number	OAL4107	OAL4104
Wattage	1.2kW	
Frequency	50Hz / 60Hz	
Cabinet Height	750mm	
Cabinet Width	707mm	
Cabinet Depth	691mm	
Cabinet Weight	80kg	
Airflow	400m3/h	
Sound Level	<60dBa	

Machine supplied with

• 1 x Main Filter • 1 x Pre-filter • 1 x Connection Kit • 1 x Power Cable • 1 x Manual

Find out more: Wpurex.co.uk | [T +44 \(0\)1405 746030](tel:+44(0)1405746030) | [E purex@purex.co.uk](mailto:purex@purex.co.uk)

Registered Office: Purex International LTD, Unit A, Saltgrounds Road, Brough, HU15 1EG, UK

Registered No. 5136616 England | VAT No. GB842 5025 49 | WEEE Producer Registration Number: WEE/CE0067TX

*Goods are subject to change | *Illustrations are 3D created visual representations

Connection kits

If you do not see a connection kit that fits your machine or pipework, please contact Purex or your representative

100032		
Hose End Diameter	Hose Length	Purex Inlet Diameter
50mm	3m	80mm

Connect to 50mm diameter pipe/port or Purex valve

3.0m

120288		
Hose End Diameter	Hose Length	Purex Inlet Diameter
100mm	2.3m	80mm

Connect to 100mm diameter pipe/port

0.3m 2.0m

120292		
Hose End Diameter	Hose Length	Purex Inlet Diameter
100mm	1.6mm	80mm

Connect to 100mm diameter pipe/port

0.3m 1.3m

LASER XBASE

120293		
Hose End Diameter	Hose Length	Purex Inlet Diameter
80mm	1.3m	80mm

Connect to 80mm diameter pipe/port

1.3m

Interfacing

Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Your Machine

10011010



10011010

Extractor

Take a look through our [Interfacing Guide](#) to see our extensive range of options