

IFUME 400i OZONE

Moderate, ozone only application extraction

PUREX
CLEAN AIR FOR EVERYONE



Description & features

- Full colour touch screen display
- Highest grade HEPA and carbon technology
- Automatic electronic flow control - maintains a constant extraction rate even as the filter blocks
- Gas and particle sensors to warn the operator
- Operate worldwide with no loss of performance
- Specialized coating to prevent corrosion

Filters



Main Filter Code

113450

Description

HEPA/Chemical



Pre-Filter Code

111097

Description

F6 Labyrinth



Pre-Filter Code

200037

Description

Chemical Absorbant Pad

Specification

Voltage	100v - 230v
Vacuum Part Number	1704132
Wattage	1.1kW
Frequency	50Hz / 60Hz
Cabinet Height	1195mm
Cabinet Width	465mm
Cabinet Depth	528mm
Cabinet Weight	70kg
Airflow	400m3/h
Sound Level	<60dBa

Machine supplied with

• 1 x Main Filter • 1 x Pre-filter • 1 x Absorbant Pad • 1 x Connection Kit • 1 x Power Cable • 1 x Manual • 1 x FMU monitor unit

Find out more: W purex.co.uk | [T +44 \(0\)1405 746030](tel:+44(0)1405746030) | [E purex@purex.co.uk](mailto:purex@purex.co.uk)

Registered Office: Purex International Limited, QWP House, Island Drive, Capitol Park, Thorne, Doncaster DN8 5UE
Registered No. 5136616 England | VAT No. GB842 5025 49 | WEEE Producer Registration Number: WEE/CE0067TX
*Goods are subject to change | *Illustrations are 3D created visual representations

IFUME 400i OZONE

Moderate, ozone only application extraction

Options

Filter Monitor Unit



Code

400470

Description

Ozone FMU


Connection kits

100043C

Hose End Diameter	Hose Length	Purex Inlet Diameter
50mm	6m	80mm

coated to prevent corrosion

Connect to 50mm diameter pipe/port or Purex valve



6.0m

120299

Hose End Diameter	Hose Length	Purex Inlet Diameter
80mm	3m	80mm

Connect to 80mm diameter pipe/port



3.0m

Interfacing

Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Your Machine

10011010



10011010

Extractor

Take a look through our [Interfacing Guide](#) to see our extensive range of options